

FEP 30 AT...JT	Gie	Si-Di	Dual, 50...600V, 30A(Tc=100°), Uf<0,95V(15A), <50ns	18e	TO-247			BYV 74/..., MUR 3005PT...3060PT
FER 8 AT...JT	Gie	Si-Di	=FES 8AT...JT:	17m	TO-220			-
FER 16 AT...JT	Gie	Si-Di	=FES 16AT...JT:	17m	TO-220			-
FES 8 AT...JT	Gie	Si-Di	P FRR, 50...600V, 8A(Tc=100°), Uf<0,95V(8A), <35ns A=50,B=100,C=150,D=200,F=300,G=400,H=500,J=600V	17k	TO-220			BYR 29/..., BYT 86/..., FE 8A...J
FES 16 AT...JT	Gie	Si-Di	FRr, 50...600V, 16A(Tc=100°), Uf< 0,98V(16A), <35ns	17k	TO-220			BYR 79/..., BYT 87/..., FE 16A...J
FF(p,s)		Si-N	=BCV 27 (SMD-Marking)	35	SOT-23			•BCV 27
FF		Si-N	=BFO 18A (SMD-Marking)	39	SOT-89			•BFO 18A
FG(p,s)		Si-N	=BCV 47 (SMD-Marking)	35	SOT-23			•BCV 47
FG		Si-N	=BFQ 149 (SMD-Marking)	39	SOT-89			•BFQ 149
FG		Si-N	=BFO 19S (SMD-Marking)	39	SOT-89			•BFO 19S
FG 1		Ge-P	=2SB33			AC 151	2a	•2SB33
FG 2 N	Fdj	Si-Di	TV Damper-Di, 300V, 1A, Uf<1,1V(2A)	31a	(6x9mmØ)	BYD 33 M	31a	BY 201/3, BYX 55/350, MR 813, RGP 10G,++
FH(s)		Si-N	=BFN 24 (SMD-Marking)	35	SOT-23			•BFN 24
FHP		Si-N	=2SC5020-P (SMD-Marking)	35(2mm)	SOT-323			•2SC5020
FHQ		Si-N	=2SC5020-Q (SMD-Marking)	35(2mm)	SOT-323			•2SC5020
FHR		Si-N	=2SC5020-R (SMD-Marking)	35(2mm)	SOT-323			•2SC5020
FI		MOS-N-FET-d	=3SK186 (SMD-Marking)	44	SOT-143			•3SK186
FI		MOS-N-FET-d	=3SK217 (SMD-Marking)	44	SOT-143			•3SK217
FJ		N-FET	=2SK1069 (SMD-Marking)	35(2mm)	SOT-323			•2SK1069
FJ(s)		Si-N	=BFN 26 (SMD-Marking)	35	SOT-23			•BFN 26
FJ 3		N-FET	=2SK771-3 (SMD-Marking)	35	SOT-23			•2SK771
FJ 4		N-FET	=2SK771-4 (SMD-Marking)	35	SOT-23			•2SK771
FJ 5		N-FET	=2SK771-5 (SMD-Marking)	35	SOT-23			•2SK771
FJ 2501		Si-P-Darl	=BDX 34A	17j	TO-220	BD 902	17j	•BDX 34(A...D)
FJ 3001		Si-N-Darl	=BDX 33A	17j	TO-220	BD 901	17j	•BDX 33(A...D)
FK		Si-P	=2SB800-FK (SMD-Marking)	39	SOT-89			•2SB800
FK(s)		Si-P	=BFN 25 (SMD-Marking)	35	SOT-23			•BFN 25
FKE 4 F2/....	Skr	Si-Di	>SKE 4F2/....	33a		SKE 4F2/10	33a	
FL		Si-P	=2SA1434 (SMD-Marking)	35	SOT-23			•2SA1434
FL		Si-P	=2SB800-FL (SMD-Marking)	39	SOT-89			•2SB800
FL(s)		Si-P	=BFN 27 (SMD-Marking)	35	SOT-23			•BFN 27
FLV....		Opto						
FM		Si-P	=2SB800-FM (SMD-Marking)	39	SOT-89			•2SB800
FM		Si-Di	=BB 804 (SMD-Marking)	35	SOT-23			•BB 804
FMA 1	Rhm	Si-P+R	SMD, Dual, Rb=Rbe=22kΩ, 50V, 30mA	45	SOT-153			-
FMA 2	Rhm	Si-P+R	SMD, Dual, Rb=Rbe=47kΩ, 50V, 30mA	45	SOT-153			-
FMA 3	Rhm	Si-P+R	SMD, Dual, Rb=4,7kΩ, Rbe=, 50/50V, 100mA	45	SOT-153			-
FMA 4	Rhm	Si-P+R	SMD, Dual, Rb=10kΩ, Rbe=, 50/50V, 100mA	45	SOT-153			-
FMA 5	Rhm	Si-P+R	SMD, Dual, Rb=2,2k, Rbe=47kΩ, 50V, 100mA	45	SOT-153			-
FMA 6	Rhm	Si-P+R	SMD, Dual, Rb=47kΩ, Rbe=, 50/50V, 100mA	45	SOT-153			-
FMC 1	Rhm	Si-N/P	SMD, NPN+PNP, Rb=4,7kΩ, Rbe=, 50/50V, 100mA	45	SOT-153			-
FMC 2	Rhm	Si-N/P	SMD, NPN+PNP, Rb=Rbe=22kΩ, 50V, 100mA	45	SOT-153			-
FMC 3	Rhm	Si-N/P	SMD, NPN+PNP, Rb=Rbe=10kΩ, 50V, 50mA	45	SOT-153			-
FMG 1	Rhm	Si-N+R	SMD, Dual, Rb=Rbe=22kΩ, 50V, 30mA	45	SOT-153			-
FMG 2	Rhm	Si-N+R	SMD, Dual, Rb=Rbe=22kΩ, 50V, 30mA	45	SOT-153			-
FMG 3	Rhm	Si-N+R	SMD, Dual, Rb=4,7kΩ, Rbe=, 50/50V, 100mA	45	SOT-153			-
FMG 4	Rhm	Si-N+R	SMD, Dual, Rb=10kΩ, Rbe=, 50/50V, 100mA	45	SOT-153			-
FMG 5	Rhm	Si-N+R	SMD, Dual, Rb=10k, Rbe=47kΩ, 50V, 100mA	45	SOT-153			-
FMG 6	Rhm	Si-N+R	SMD, Dual, Rb=47kΩ, Rbe=, 50/50V, 100mA	45	SOT-153			-
FMG 7	Rhm	Si-N+R	SMD, Dual, Rb=10kΩ, Rbe=, 50/50V, 100mA	45	SOT-153			-
FMG 8	Rhm	Si-N+R	SMD, Dual, Rb=4,7k, Rbe=47kΩ, 50V, 100mA	45	SOT-153			-
FMMT 918	Fer	Si-N	=2N918: SMD	35a	SOT-23			BF 517, BFS 17, 2SC3016, 2SC3061, ++
FMMT 2222(A)	Fer	Si-N	=2N2222(A): SMD	35a	SOT-23			BSR14, BSS79, PMBT2222(A), SMBT2222(A)
FMMT 2222(A)R	Fer	Si-N	=2N2222(A): SMD	35d	SOT-23			-
FMMT 2369(A)	Fer	Si-N	=2N2369(A): SMD	35a	SOT-23			2SC4168, PMBT 2369(A)
FMMT 2484	Fer	Si-N	=2N2484: SMD	35a	SOT-23	BC 850	35a	BC 850, 2SC3323
FMMT 2907(A)	Fer	Si-P	=2N2907(A): SMD	35a	SOT-23			BSR15...16,BSS80,PMBT2907(A),SMBT2907(A)
FMMT 2907(A)R	Fer	Si-P	=2N2907(A): SMD	35d	SOT-23			-
FMMT 3903...3904	Fer	Si-N	=2N3903...3904: SMD	35a	SOT-23	BC 846	35a	BC846, BCV71...72, PMBT3903...3904, SMBT3904
FMMT 3905...3906	Fer	Si-P	=2N3905...3906: SMD	35a	SOT-23	BC 856	35a	BC856...857, BCX71, PMBT3905...3906, SMBT3906
FMMT 4124	Fer	Si-N	=2N4124: SMD	35a	SOT-23	BC 846	35a	BC 846...848, BSR 17, SMBT 4124, 2SC3392
FMMT 4125	Fer	Si-P	=2N4125: SMD	35a	SOT-23	BC 856	35a	BC 856...858, BSR 18, SMBT 2126, 2SA1607
FMMT 5087	Fer	Si-P	=2N5087: SMD	35a	SOT-23	BC 860	35a	BC 860, BCF 70, SMBT 5087, 2SA1311
FMMT 5087 R	Fer	Si-P	=2N5087: SMD	35a	SOT-23			-
FMMT-A05...06	Fer	Si-N	=MPS-A05...06: SMD	35a	SOT-23			BCW 65...66, PMBT-A05...06, SMBTA 05...06++
FMMT-A12...14	Fer	Si-N-Darl	=MPS-A12...14: SMD	35a	SOT-23			BCV 27, PMBT-A12...14, SMBTA 13...14++
FMMT-A20	Fer	Si-N	=MPS-A20: SMD	35a	SOT-23	BC 846	35a	BC 846...847, BCW 71...72, SMBTA 20, ++
FMMT-A42...43	Fer	Si-N	=MPS-A42...43: SMD	35a	SOT-23			PMBT-A42...43, SMBTA 42...43
FMMT-A42R...43R	Fer	Si-N	=MPS-A42...43: SMD	35d	SOT-23			-
FMMT-A55...56	Fer	Si-P	=MPS-A55...56: SMD	35a	SOT-23			BCW 68, BCX 42, PMBT-A55...56, SMBTA 55...56++
FMMT-A70	Fer	Si-P	=MPS-A50: SMD	35a	SOT-23	BC 856	35a	BC 856...857, BCW 69...70, 2SA1311, ++
FMMT-A92...93	Fer	Si-P	=MPS-A92...93: SMD	35a	SOT-23			PMBT-A92...93, SMBTA 92...93
FMMT-A92R...93R	Fer	Si-P	=MPS-A92...93: SMD	35d	SOT-23			-
FMP 18 N05	Fch	MOS-N-FET-e	VFET, 50/30V, 18/50A, 75W, on<0,1Ω(10A)	17p	TO-220			BUZ 21...22, IRF 540...43, 2SK674, 2SK1417
FMP 20 N05	Fch	MOS-N-FET-e	VFET, 50/30V, 20/60A, 75W, <85mΩ(10A), <140/135ns	17p	TO-220			BUZ 21...22, IRF 540...43, 2SK674, 2SK1417
FMP 30 N05	Fch	MOS-N-FET-e	VFET, 50/30V, 30A, 100W, on=0,05Ω	17p	TO-220			BUK 555/50, BUZ 11...12, PRFZ 42, 2SK856+
FMP 35 N05	Fch	MOS-N-FET-e	VFET, 50/30V, 35A, 100W, on=0,04Ω	17p	TO-220			BUK 555/50, BUZ 11...12, PRFZ 42, 2SK856+
FMPS-A 05	Fch	Si-N	=MPS-A05	7e	TO-92	→MPS-A05		•MPS-A05
FMPS-A 06	Fch	Si-N	=MPS-A06	7e	TO-92	→MPS-A06		•MPS-A06
FMPS-A 55	Fch	Si-P	=MPS-A55	7e	TO-92	→MPS-A55		•MPS-A55
FMPS-A 56	Fch	Si-P	=MPS-A56	7e	TO-92	→MPS-A56		•MPS-A56
FMS 1	Rhm	Si-P	SMD, Dual, Uni, 50/40V, 100mA	45	SOT-153			-
FMS 2	Rhm	Si-P	SMD, Dual, Uni, 50/40V, 100mA	45	SOT-153			-
FMS 3	Rhm	Si-P	SMD, Dual, Uni, 120/120V, 50mA	45	SOT-153			-
FMS 4	Rhm	Si-P	SMD, Dual, Uni, 120/120V, 50mA	45	SOT-153			-
FMW 1	Rhm	Si-N	SMD, Dual, Uni, 50/40V, 100mA	45	SOT-153			-
FMW 2	Rhm	Si-N	SMD, Dual, Uni, 50/40V, 100mA	45	SOT-153			-
FMW 3	Rhm	Si-N	SMD, Dual, Uni, 120/120V, 50mA	45	SOT-153			-
FMW 4	Rhm	Si-N	SMD, Dual, Uni, 120/120V, 50mA	45	SOT-153			-
FMW 5	Rhm	Si-N	SMD, Dual, Uni, 50/40V, 100mA	45	SOT-153			-
FMW 6	Rhm	Si-N	SMD, Dual, HF, 30/18V, 50mA, >600MHz	45	SOT-153			-