

2 SC 4070	Say	Si-N+R	S,50/50V, 0,1/0,2A, 0,3W, 250MHz, Rbe=22kΩ	{2SA1574	41c		(BC 546) <sup>18</sup>	7a	-
2 SC 4071	Say	Si-N	Dual, 30/20V, 0,03A, 0,25W, 1200MHz, ΔUbe<10mV						-
2 SC 4072	Say	Si-N	Dual, 25/16V, 0,05A, 0,25W, 3500MHz, <ΔUbe<10mV						-
2 SC 4073	Sak	Si-N	S-Reg, 500/400V, 5/10A, 30W, 10MHz, <1/3,5μs		17c	TO-220 Iso	2SC3795	17c	BUT 11(A)F, 2SC3570, 2SC3573, 2SC4054, ++
2 SC 4074	Rhm	Si-N	SMD, VHF/UHF, 30V, 0,05A, 1500MHz		35a	SOT-23			BFR 53, 2SC3014, 2SC3016
2 SC 4075	Say	Si-N	CTV LF, Vid, 300/300V, 0,2/0,7A, 10W, >50MHz		17c	TO-220 Iso	(2SC1505) <sup>3</sup>	17j	2SC3565, (2SC1505...07, 2SC1755...57, ++) <sup>3</sup>
2 SC 4076	Rhm	Si-N	SMD, Uni, 60/50V, 0,15A, 180MHz		35a	SOT-23	BC 846	35a	BC 846, BCV 71...72, 2SC3323
2 SC 4077	Rhm	Si-N	LF, In, 30/30V, 0,1A, 0,3W, 230MHz, F=3dB(120Hz)		7c	TO-92	BC 550	7a	BC 169, BC 184, BC 239, BC 549, ++
2 SC 4078	Rhm	Si-N	=2SC4077:		9c		BC 550	7a	BC 169, BC 184, BC 239, BC 549, ++
2 SC 4079	Rhm	Si-N	=2SC4077: SMD		35a	SOT-23	BC 850	35a	BC 849...850, BCF 32...33, BCF 81, 2SC3323
2 SC 4080	Say	Si-N	SMD, Vid, 200/200V, 0,1/0,2A, 400MHz	{2SA1575	39b	SOT-89			-
2 SC 4081	Rhm	Si-N	=2SC2412K:		35a(2mm)	SOT-323			2SC4128, 2SC4155
2 SC 4082	Rhm	Si-N	=2SC3837K:		35a(2mm)	SOT-323			-
2 SC 4083	Rhm	Si-N	=2SC3838K:		35a(2mm)	SOT-323			-
2 SC 4084	Rhm	Si-N	=2SC3839K:		35a(2mm)	SOT-323			-
2 SC 4085	Nec	Si-N	SMD, VHF/UHF, 30/25V, 0,02A, 1000MHz		44o	SOT-143			2SC4086...4087
2 SC 4086	Nec	Si-N	SMD, UHF, 30/15V, 0,05A, 2000MHz		44o	SOT-143			2SC4087
2 SC 4087	Nec	Si-N	SMD, UHF, 30/14V, 0,05A, 2000MHz		44o	SOT-143			2SC4086
2 SC 4088	Nec	Si-N	SMD, UHF, 15/8V, 5mA, 4000MHz		44o	SOT-143			2SC4089
2 SC 4089	Nec	Si-N	SMD, UHF, 25/12V, 0,03A, 4000MHz		44o	SOT-143			-
2 SC 4090	Nec	Si-N	SMD, UHF, 30/14V, 0,05A, 2000MHz		44u	SOT-143			2SC4092
2 SC 4091	Nec	Si-N	SMD, UHF, 15/8V, 5mA, 4000MHz		44u	SOT-143			2SC4092
2 SC 4092	Nec	Si-N	SMD, UHF, 25/12V, 0,07A, 6GHz, Gp=14,5dB(1GHz)		44u	SOT-143			2SC4093
2 SC 4093	Nec	Si-N	SMD, UHF, 20/12V, 0,1A, 6,5GHz		44u	SOT-143			-
2 SC 4094	Nec	Si-N	SMD, UHF, 20/10V, 65mA, 9GHz, Gp=17dB(1GHz)		44u	SOT-143			-
2 SC 4095	Nec	Si-N	SMD, UHF, 20/10V, 35mA, 10GHz, Gp=12dB(2GHz)		44u	SOT-143			-
2 SC 4096	Mat	Si-N	S P, 1400/800V, 10/15A, 150W, 13MHz, 1/3,8μs		77j	TOP-3L			2SC3995
2 SC 4097	Rhm	Si-N	=2SC2411K:	{2SA1577	35a(2mm)	SOT-323			2SD1949
2 SC 4098	Rhm	Si-N	=2SC2413K:		35a(2mm)	SOT-323			2SC4128, 2SC4155
2 SC 4099	Rhm	Si-N	=2SC2059K:		35a(2mm)	SOT-323			-
2 SC 4100	Rhm	Si-N	=2SC3082K:		35a(2mm)	SOT-323			-
2 SC 4101	Rhm	Si-N	SMD, LF In, 120/120V, 50mA, 140MHz, F=0,2dB(100Hz)		35a(2mm)	SOT-323			2SC3324, 2SD814(A)
2 SC 4102	Rhm	Si-N	=2SC3906K:	{2SA1579	35a(2mm)	SOT-323			-
2 SC 4103	Rhm	Si-N	=2SC3802K:		35a(2mm)	SOT-323			-
2 SC 4104	Say	Si-N	SMD, Vid, 70/60V, 50/100mA, 700MHz	{2SA1580	35a	SOT-23			-
2 SC 4105	Say	Si-N	S P, 500/400V, 4/8A, 40W, 20MHz, <500/2800ns		17j	TO-220	BUT 11 A	17j	BUT 11(A), TIP 75C, 2SC3038, 2SC3497, ++
2 SC 4106	Say	Si-N	S P, 500/400V, 7/14A, 50W, 20MHz, <500/2800ns		17j	TO-220	BUT 56 A	17j	BUT 54, BUT 56(A), 2SC3170, 2SC4055, ++
2 SC 4107	Say	Si-N	S P, 500/400V, 10/20A, 60W, 20MHz, <500/2800ns		17j	TO-220	BUT 76 A	17j	BUT 76(A), BUW 56(A), 2SC3562, 2SC4164, ++
2 SC 4108	Say	Si-N	S P, 500/400V, 12/25A, 100W, 20MHz, <500/2800ns		18j	TO-3P	BUW 13 A	18j	BUW 48(A...C), BUW 13(A), 2SC3520, 2SC4140, ++
2 SC 4109	Say	Si-N	S P, 500/400V, 16/32A, 140W, 20MHz, <500/2800ns		18j	TO-3P			BUX 98(A)P, 2SC3850
2 SC 4110	Say	Si-N	S P, 500/400V, 25/40A, 160W, 20MHz, <500/2800ns		18j	TO-3P			BUX 98P
2 SC 4111	Mat	Si-N	S P, 1500/700V, 10/22A, 150W, 2MHz, <1/12,6μs		77j	TOP-3L			2SC3995
2 SC 4112	Say	Si-N+R	=2SC4113: SMD	{2SA1581	35a	SOT-23			-
2 SC 4113	Say	Si-N+R	S,50/50V, 0,1/0,2A, 0,3W, 250MHz, Rb=2,2kΩ	{2SA1582	41c		(BC 546) <sup>18</sup>	7a	-
2 SC 4114	Mat	Si-N	SMD, 600/550V, 0,1A, <2/5,5μs		39b	SOT-89			-
2 SC 4115(S)	Rhm	Si-N	L.F.S, 40/20V, 2/5A, 0,4W, 290MHz		41c	(SPT)	2SC3225	7c(9mm)	2SC3225, 2SD1055, 2SD1227, 2SD2177, ++
2 SC 4116	Tos	Si-N	SMD, Uni, In, 60/50V, 0,15A, >80MHz	{2SA1586	35a(2mm)	SOT-323			-
2 SC 4117	Tos	Si-N	SMD, Uni, In, 120/120V, 0,1A, 100MHz	{2SA1587	35a(2mm)	SOT-323			2SC4101...4102
2 SC 4118	Tos	Si-N	SMD, Uni, 35/30V, 0,5A, 300MHz	{2SA1588	35a(2mm)	SOT-323			2SC4097
2 SC 4119	Say	Si-N-Dar+Di	S P, 1500/800V, 15/30A, 250W, hFE>25		77j	TOP-3L			-
2 SC 4120	Say	Si-N+R	=2SC4121: SMD	{2SA1589	35a	SOT-23			KSR 1111
2 SC 4121	Say	Si-N+R	S,50/50V, 0,1/0,2A, 0,3W, 250MHz, Rb=22kΩ	{2SA1590	41c		(BC 546) <sup>18</sup>	7a	KSR 1011
2 SC 4122	Say	Si-N+Di	HA, hi-def, 1500/800V, 6A, 60W, sat<5V(4A)		18c	TO-3P Iso	(BU 508 DF)	16c	2SC4294, (BU 508DF, 2SD1556, 2SD1652)
2 SC 4123	Say	Si-N+Di	HA, hi-def, 1500/800V, 7/16A, 60W, sat<5V(5A)		18c	TO-3P Iso	(BU 508 DF)	16c	(BU 508DF)
2 SC 4124	Say	Si-N+Di	HA, hi-def, 1500/800V, 8A, 70W, sat<5V(6A)		18c	TO-3P Iso	(BU 508 DF)	16c	(BU 508DF)
2 SC 4125	Say	Si-N+Di	HA, hi-def, 1500/800V, 10/25A, 70W, sat<5V(8A)		18c	TO-3P Iso			(2SC3684) <sup>3</sup>
2 SC 4126	Hit	Si-N	SMD, UHF, 15/11V, 50mA, 6GHz, F=1,5/Gp=11dB(900MHz)		44u	SOT-143			2SC4092
2 SC 4127	Hit	Si-N	SMD, UHF, 15/10V, 50mA, 7,5GHz, F=1,2/Gp=12dB(900M)		44u	SOT-143			2SC4094
2 SC 4128	Rhm	Si-N	=2SC4018K:		35a(2mm)	SOT-323			2SC4081, 2SC4141, 2SC4155
2 SC 4129	Rhm	Si-N	S P, 400/400V, 5A, 30W, 15MHz, <1/3,5μs		17c	SOT-186	BUT 11 AF	17c	BUT 11(A)F, 2SC3570, 2SC3573, 2SC4073, ++
2 SC 4130	Sak	Si-N	S P, 500/400V, 7/14A, 30W, 15MHz, <1/2,7μs		17c	TO-220 Iso	(BUT 56 A) <sup>3</sup>	17j	2SC3571, 2SC3574, 2SC3890, 2SC4056, ++
2 SC 4131	Sak	Si-N	100/50V, hi-Ueb=15V, 15/25A, 60W, 18MHz, 0,5/2,4μs		18c	=TO-3P Iso	(BD 249 C) <sup>3</sup>	18j	(BD 545C, BD 745C, 2SD1840) <sup>3</sup>
2 SC 4132	Rhm	Si-N	SMD, S, 120/120V, 2/3A, 80MHz		39b	SOT-89			2SC3649, 2SD1420...1421
2 SC 4133	Say	Si-N+R	S, 50/50V, 0,1/0,2A, 250MHz, Rb=4,7k, Rbe=47kΩ		41c		(BC 546) <sup>18</sup>	7a	2SC4195
2 SC 4134	Say	Si-N	P, 120/100V, 1/2A, 10W, 120MHz, 80/900ns	{2SA1591	30j	TO-251/252	2SC4135	30j	2SD1074...75, 2SD1283...84
2 SC 4135	Say	Si-N	P, 120/100V, 2/3A, 15W, 120MHz, 80/1050ns	{2SA1593	30j	TO-251/252	2SC4135	30j	2SD1815...16
2 SC 4136	Fjd	Si-N	S P, 200/120V, 20A, 140W, <0,5/2μs		23a	TO-3			BUW 11, BUW 58, BUX 11, 2SC2865(A), ++
2 SC 4137	Rhm	Si-N	25/20V, 0,1/0,2A, 400MHz, hFE=560...2700		14b	TO-126 Iso			-
2 SC 4138	Sak	Si-N	S-Reg, 500/400V, 10/20A, 80W, 10MHz, <1/3,5μs		18j	TO-3P	BUW 13 A	18j	BUW 48(A...C), BUW 13(A), 2SC3042, ++
2 SC 4139	Sak	Si-N	S-Reg, 500/400V, 15/30A, 120W, 10MHz, <1/3,5μs		18j	TO-3P	BUW 13 A	18j	BUW 48(A...C), BUW 13(A), 2SC3520, ++
2 SC 4140	Sak	Si-N	S-Reg, 500/400V, 18/36A, 130W, 10MHz, <1/3,5μs		18j	TO-3P			BUX 98AP, 2SC3850, 2SC4110
2 SC 4141	Rhm	Si-N	SMD, Uni, 60/50V, 0,1A, 180MHz		35a(2mm)	SOT-323	BC 846	35a	BC 846, BCV 71...72, 2SC3639, 2SC4116, ++
2 SC 4142	Hit	Si-N	TV-HA, 1500/800V, 5A, 50W, <0,5/4,5μs		18c	TO-3P Iso	BU 508 AF	16c	BU 508AF, 2SD1545...46, 2SD1655...56, ++
2 SC 4143	Hit	Si-N	TV-HA, 1500/800V, 5A, 50W, <0,5/4,5μs		18c	TO-3P Iso	BU 508 AF	16c	BU 508AF, 2SD1545...46, 2SD1655...56, ++
2 SC 4144	Hit	Si-N	TV-HA, 1300/500V, 8A, 50W, <0,5/3,4μs		18c	TO-3P Iso	BU 508 AF	16c	BU 508AF, BU 908F, 2SD1548
2 SC 4145	Rhm	Si-N	L.F.S, 80/80V, 2A, 1,2W, <1/4μs		7c(9mm)	TO-92L	(2SC4135) <sup>4</sup>	30j	2SC3328, 2SC3669, 2SD1015, 2SD2182
2 SC 4146	Say	Si-N+R	=2SC4133: SMD	{2SA1597	35a	SOT-23			-
2 SC 4147	Rhm	Si-N	HF, Vid P, 300/300V, 0,1A, 5W, 100MHz		≈14h	SOT-82	BF 459	14h	BF 417, BF 459, 2SC3417, 2SC3503, ++
2 SC 4148	Shi	Si-N	S P, 60/40V, 7A, 25W, <0,3/2μs, sat<0,3V	{2SA1598	15c	(ITO-220)			2SC3747
2 SC 4149	Shi	Si-N	S P, 60/40V, 10A, 25W, <0,3/2μs, sat<0,3V	{2SA1599	15c	(ITO-220)			2SC3748
2 SC 4150	Shi	Si-N	S P, 60/40V, 12A, 25W, <0,3/2μs, sat<0,3V	{2SA1600	15c	(ITO-220)			2SC3709, 2SC4065
2 SC 4151	Shi	Si-N	S P, 60/40V, 15A, 30W, <0,3/2μs, sat<0,3V	{2SA1601	15c	(ITO-220)			2SC3694, 2SC4552
2 SC 4152	Mat	Si-N	S P, 1400/700V, 0,3/1A, 20W, 12MHz, <2/4μs		17c	SOT-186			-
2 SC 4153	Sak	Si-N	S P, 200/120V, 7/14A, 30W, 30MHz, <0,5/3,5μs		17c	TO-220 Iso			2SD1792
2 SC 4154	Mit	Si-N	=2SC3052:	{2SA1602	35a(2mm)	SOT-323			2SC4076, 2SC4116
2 SC 4155	Mit	Si-N	=2SC3928:	{2SA1603	35a(2mm)	SOT-323	BC 846	35a	BC 846...847, 2SC4081, 2SC4128, 2SC4141, ++
2 SC 4156	Say	Si-N	Dual, 60/50V, 0,5A, 0,4W, 300MHz, ΔUbe<10mV	{2SA1604					-
2 SC 4157	Tos	Si-N	S P, 600V/450V, 10/20A, 100W, <0,5/3μs		18j	TO-3P			BUW 47(A), BUW 12(A), 2SC3831, ++
2 SC 4158	Mat	Si-N	Vid Out, 250/250V, 0,1/0,2A, 300MHz, 8W		17c	SOT-186	(2SC1505) <sup>3</sup>	17j	2SC3565, 2SC4075, (2SC1505...1507, ++) <sup>3</sup>
2 SC 4159	Say	Si-N	P, 180/160V, 1,5/3A, 15W, 100MHz	{2SA1606	17c	TO-220 Iso	2SC4159	17c	2SC3298A,B
2 SC 4160	Say	Si-N	=2SC4105: Iso, 25W		17c	TO-220 Iso	BUT 11 AF	17c	BUT 11(A)F, 2SC3573, 2SC4054, 2SC4073, ++
2 SC 4161	Say	Si-N	=2SC4106: Iso, 30W		17c	TO-220 Iso	(BUT 56 A) <sup>3</sup>	17j	2SC3571, 2SC3574, 2SC4056, 2SC4130, ++